

July 1960




FIGURE 1 – Frequency Response
(average axis pressure under anechoic conditions)

DESCRIPTION AND APPLICATIONS

The Electro-Voice Sentry IVA incorporates many new and innovative design ideas which represent a significant advance in state-of-the-art speaker design. The 3-way, all horn loaded system offers absolute minimum distortion through all frequencies while providing unequalled efficiency and uniformity over the entire frequency range. With high power handling capacity, extremely uniform and wide dispersion, and linear frequency response, the Sentry IVA offers versatility for applications in not only studio monitoring, but in high level sound reinforcement, high level playback systems, etc.

The midrange and tweeter horn designs represent the first significantly new sectoral design in 25 years. With vertical dispersion of greater than 60-degrees at all frequencies and extremely stable horizontal dispersion at 120-degrees virtually throughout the frequency range, these horns offer a uniformity of coverage which practically eliminate "hot spots" and "dead areas" in the control room or elsewhere (See Figure 2). Totally new drivers are associated with the midrange and high-frequency components to offer both ruggedness and linear response.

The woofer section also utilizes the folded horn principle for increased efficiency and lower distortion. The design of the enclosure permits linear low-frequency response to within a few cycles of the theoretical enclosure cutoff

frequency of 50 Hz. Two 12-inch cone drivers are used in the folded horn low-frequency section.

The crossover provides push clip terminals for connection of all components.

A female phone plug receptacle is provided for biamping high-frequency input. For those who wish to use an active crossover, all high-frequency information should be routed into the crossover via this receptacle. In this way the crossover between woofer and midrange (400 Hz) is bypassed.

A high-frequency rolloff attenuator is provided on the crossover which increases effective power handling capacity by smoothly attenuating tweeter input power.

SPECIFICATIONS

- Frequency Response:** 50 to 18,000 Hz (See Fig. 1)
- EIA Sensitivity (on axis measurements):** 52 dB
- Sound Pressure Level (4' on axis, 50 W):** 117 dB
- Impedance:** 8 ohms nominal
- Power Handling Capacity:** 50 W (see explanation)
- Finish:** Utility Black
- Size:** 27¾" w (70.5cm) x 20-5/8" d. (52.3cm) x 50¾" h. (129cm) - in normal configuration
- Weight:** 148 pounds (67 Kg)

POWER HANDLING CAPACITY

In an effort to provide a meaningful power rating, the frequency spectrum of the lead guitar in several prominent groups was band-analyzed. A filter was designed that would shape white noise (a sound similar to between-station FM noise, consisting of all frequencies from 20 to 20,000 Hz simultaneously) to the typical lead guitar spectrum. The lead guitar frequency spectrum is far more demanding at the frequency extremes than voice or conventional music program material. Filtered white noise

is fed into the system at various levels to determine the power handling capacity.

With the attenuator in the No. 1 position (flat) the continuous power handling capacity (above defined and assuming a nominal 8 ohm load) is 50 watts. With the attenuator in the No. 2 position, the power handling is 75 watts continuous. In No. 3 position, it is 125 watts continuous. The fourth attenuator position almost completely attenuates the upper range of the tweeter output and significantly increases power handling capacity.

Figure 6 shows continuous sine wave power handling with relation to frequency. The graph is designed to be used to calculate power handling when unusual program sources with substantial high frequency energy are anticipated. *A continuous voltage of 4 volts into the tweeter should not be exceeded when using noise inputs.*

CAUTION: While the normal area of maximum peak power in program material tends to be in the 500 Hz range, fast winding of professional tape machines at five to six times the normal speed shifts the peak power area into the tweeter which, in effect, causes the tweeter to function as a full-range speaker. In addition to shifting the power spectrum, transient times are accelerated and destructive forces are substantially increased. *The tweeter will not tolerate much of this type of treatment*, so care should be taken when high winding to assure that the tape is lifted from the playback head.

CONNECTING THE SENTRY IVA

The Sentry IVA is shipped in two separate packages. After unpacking the low-frequency section, the high-frequency subassembly may be unpacked and assembled. Two brackets are shipped with the high-frequency assembly which, by means of the hardware provided, attach the tweeter to the midrange horn (see Figure 3). You may notice that the predrilled holes in the front of the midrange horn do not align with the predrilled holes in the tweeter mounting bracket. With the hands, the horn mouth should be stretched or compressed so that the predrilled horn holes match the tweeter bracket holes. The brackets should then be screwed in place. (The above operation insures that the horn mouth area and horn rigidity are maintained constant, as designed.)

The tweeter may be suspended below the midrange horn or above it, depending on final mounting configuration. In the normal mounting configuration, the midrange/crossover assembly is secured to the top of the low-frequency section, and the tweeter is suspended below the midrange section hanging in the upper wave path of the low-frequency section. Hinges are provided by which, with shims, the high-frequency assembly can be tilted and affixed at the desired angle with relation to the low-frequency assembly.

ELECTRICAL CONNECTIONS

The crossover section is shipped with the midrange driver already wired and the leads for the tweeter and the




FIGURE 2 - Frequency Dispersion

low-frequency section already attached. The white striped lead corresponds to the positive terminal (T1) on both tweeter and midrange driver, and the woofer connection is provided for with a phone plug. (Phone plug tip corresponds to positive or T1 terminal, while the sleeve is the negative terminal.) When designing or employing a low-level crossover in bi-amping, the following criteria should be used:

Crossover frequency - 400 to 450 Hz.

Crossover sloping - 12 dB per octave or greater.

Phasing - In the classical configuration for the 12 dB per octave crossover, the woofer should be connected out of phase with the high-frequency components. However, since phasing conditions in an unspecified electrical crossover cannot be anticipated, the following procedure is recommended for optimum phasing in any given situation: introduce a sine wave at the crossover frequency (between 400 and 450 Hz depending on the crossover) to the system. By switching phasing of the high-frequency half of the system, select the phasing configuration which gives the loudest output at any given crossover frequency.

In the event that this wiring is disconnected for one reason or another, it must be noted that the tweeter and midrange sections should be connected in phase with one another while the low-frequency section should be out of phase with the tweeter and midrange. Output leads (power leads) from the amplifier should be connected at the input terminals with the positive lead connected to the red input terminal, causing the low-frequency section to be in phase with the amplifier output. (See Figure 5.)

**WHEN TWO SIGNALS
DIFFER BY:**

- 0 dB
- 1
- 2
- 3
- 4
- 5
- 6
- 7
- 8
- 9
- 10
- 11
- 12

**ADD TO THE
LARGER READING**

- 3.00 dB
- 2.50
- 2.10
- 1.70
- 1.40
- 1.10
- .97
- .79
- .63
- .51
- .43
- .35
- .26


ENVIRONMENT

The Sentry IVA professional system was designed for one-quarter to one-half-space use. The unit should be as close to reflecting planes as possible so that out of phase low-frequency irregularities from the reflected wave may be avoided. Cavities around the device are undesirable, as cavity resonances may be excited.

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The speaker is a 3-way all-horn-loaded wide-range system with high power-handling capacity. Low end should consist of a folded horn housing two 12" cone drivers. Midrange should consist of a 120° sectoral horn and driver, and the high end should consist of a 120° sectoral tweeter with integral driver. Electrical crossover frequencies should be at 400 Hz and at 3500 Hz. Low-frequency cutoff should occur at approximately 50 Hz. Frequency response should be smooth and flat (in ¼- to ½-space coupling) from 50 Hz to 18,000 Hz. Dispersion of the system should be uniform with no lobes from 600 Hz to 18,000 Hz. Horizontal dispersion should be 120°, with vertical dispersion at 60°.

A tweeter protector is provided to save the tweeter from surges of excess power such as feedback and some forms



of program material. It automatically disconnects the tweeter as power exceeds the tweeter's power handling capacity (See Figure 6) and reconnects the tweeter when power levels are safe.

In the crossover No. 1 position, power handling should be 50 watts continuous (8 ohm nominal load) using a suitable noise input shaped to the lead guitar spectrum; No. 2 position, 75 watts; No. 3 position, 125 watts, and No. 4 substantially higher.

WARRANTY

Electro-Voice Sentry Loudspeakers and accessories are guaranteed for five years from date of original purchase against malfunction due to defects in workmanship and materials. If such malfunction occurs, unit will be repaired or replaced (at our option) without charge for materials or labor if delivered prepaid to the proper Electro-Voice service facility. Unit will be returned prepaid. Warranty does not cover finish or appearance items or malfunction due to abuse or operation at other than specified conditions. Repair by other than Electro-Voice or its authorized service agencies will void this guarantee.

For correct shipping address and instructions on return of Electro-Voice products for repair and locations of authorized service agencies, please write: Service Department, Electro-Voice, Inc., 600 Cecil Street, Buchanan, Michigan 49107 (Phone: 616/695-6831).

Electro-Voice also maintains complete facilities for non-warranty service.




FIGURE 7 - Nomographs