
2-WAY MODE

DATE: 01-30-95

AUTHOR: Chris Stirling

SOFTWARE

TITLE: SH1502ER + S181

VERSION: V 1.00

SPEAKER SYSTEM NAME: SH1502ER + S181

PARAMETER	INPUT	CH 1	CH 2	CH 3	CH 4
MASTER DELAY		2 ms			
MASTER PEQ FREQ		1000 Hz			
MASTER PEQ Q		1.0			
MASTER PEQ GAIN		0 dB			
LO-CUT FREQ		46 Hz		46 Hz	
LO-CUT RESP		12 dB 1.5 Q		12 dB 1.5 Q	
LOSHELV FREQ			52 Hz		52 Hz
LOSHELV SLOPE			12 dB		12 dB
LOSHELV GAIN			+6 dB		+6 dB
HI-PASS FREQ			125 Hz		125 Hz
HI-PASS RESP			4th LW		4th LW
PEQ1 FREQ		72 Hz	270 Hz	72 Hz	270 Hz
PEQ1 Q		2.1	0.7	2.1	0.7
PEQ1 GAIN		0 dB	0 dB	0 dB	0 dB
PEQ2 FREQ			2500 Hz		2500 Hz
PEQ2 Q			3.7		3.7
PEQ2 GAIN			0 dB		0 dB
LO-PASS FREQ		125 Hz		125 Hz	
LO-PASS RESP		4th LW		4th LW	
HISHELV FREQ			1000 Hz		1000 Hz
HISHELV SLOPE			thru		thru
HISHELV GAIN			0 dB		0 dB
DELAY ALIGNM			0 us	0 us	0 us
POLARITY		+	+	+	+
OUTPUT GAIN		0 dB	-6 dB	0 dB	-6 dB
LIMIT THRESH		21 dBu	21 dBu	21 dBu	21 dBu
LIMIT DECAY		50 dB/s	50 dB/s	50 dB/s	50 dB/s
LIMIT HOLD		10 ms	0 ms	10 ms	0 ms
