

DATE: 09/11/97

AUTHOR: Jeff Morton Settings were determined by Kirk Lombardo

TITLE: Sx500 settings

SPEAKER SYSTEM NAME: Sx500

SOFTWARE VERSION: 1.00

PARAMETER		CH 1	CH 2	CH 3	CH 4
MASTER DELAY	2 ms				
MASTER PEQ FREQ	980 Hz				
MATER PEQ Q	5.0				
MASTER PEQ GAIN	-3 dB				
LO-CUT FREQ		45 Hz		Hz	
LO-CUT RESP		12 dB 1.5 Q		dB Q	
LOSHLV FREQ		Hz		Hz	
LOSHLV SLOPE		dB		dB	
LOSHLV GAIN		0 dB		dB	
HI-PASS FREQ			1,600 Hz		Hz
HI-PASS RESP			Link-Riley 24dB		
PEQ1 FREQ		540 Hz	Hz	Hz	Hz
PEQ1 Q		1.9			
PEQ1 GAIN		+2 dB	0 dB	dB	dB
PEQ2 FREQ			15,600 Hz		Hz
PEQ2 Q			0.6		
PEQ2 GAIN			+8 dB		dB
LO-PASS FREQ		1,480 Hz		Hz	
LO-PASS RESP		Link-Riley 24dB			
HISHLV FREQ			10,400 Hz		Hz
HISHLV SLOPE			12 dB		dB
HISHLV GAIN			+3 dB		dB
DELAY ALIGNM		0 us	341 us	us	us
POLARITY		+	+		
OUTPUT GAIN		0 dB	-8 dB	dB	dB
LIMIT THRESH		21 dBu	21 dBu	dBu	dBu
LIMIT DECAY		50 dB/s	50 dB/s	dB/s	dB/s
LIMIT HOLD		5 ms	5 ms	ms	ms