

4-WAY MODE

DATE: 01-13-95

AUTHOR: David Carlson

SOFTWARE
VERSION: V 1.00

TITLE: MT-4A

SPEAKER SYSTEM NAME: MT-4A

PARAMETER	INPUT	CH 1	CH 2	CH 3	CH 4
MASTER DELAY		2 ms			
LO-CUT FREQ		37 Hz			
LO-CUT RESP		12 dB	1.5 Q		
LOSHELV FREQ			80 Hz		
LOSHELV SLOPE			6 dB		
LOSHELV GAIN			0 dB		
HI-PASS FREQ			160 Hz	1600 Hz	8000 Hz
HI-PASS RESP			4th LW	4th LW	4th LW
PEQ1 FREQ		80 Hz	400 Hz	3200 Hz	3600 Hz
PEQ1 Q		1.0	1.0	0.7	0.7
PEQ1 GAIN		0 dB	-2 dB	-9 dB	-7 dB
PEQ2 FREQ				16000 Hz	16000 Hz
PEQ2 Q				2.0	2.0
PEQ2 GAIN				+12 dB	+12 dB
LO-PASS FREQ		160 Hz	1600 Hz	8000 Hz	
LO-PASS RESP		4th LW	4th LW	4th LW	
HISHELV FREQ					10000 Hz
HISHELV SLOPE					6 dB
HISHELV GAIN					+2 dB
DELAY ALIGNM			3307 us	0 us	427 us
POLARITY		+	+	+	+
OUTPUT GAIN		+2 dB	-5 dB	+3 dB	+3 dB
LIMIT THRESH		21 dBu	21 dBu	21 dBu	21 dBu
LIMIT DECAY		50 dB/s	50 dB/s	50 dB/s	50 dB/s
LIMIT HOLD		0 ms	0 ms	0 ms	0 ms