

3-WAY MODE

DATE: 01-17-95

AUTHOR: Kirk Lombardo

SOFTWARE
VERSION: V 1.00

TITLE: T53 + T18

SPEAKER SYSTEM NAME: T53 + T18

PARAMETER	INPUT	CH 1	CH 2	CH3	CH4
MASTER DELAY 1-3	2.0 ms				
LO-CUT FREQ	32 Hz				
LO-CUT RESP	12 dB 0.7 Q				
LO-SHELV FREQ	80 Hz				
LO-SHELV SLOPE	6 dB				
LO-SHELV GAIN	+1 dB				
HI-PASS FREQ	116 Hz 500 Hz				
HI-PASS RESP	4th LW 4th LW				
PEQ1 FREQ	156 Hz 580 Hz 2800 Hz				
PEQ1 Q	3.0 3.4 3.5				
PEQ1 GAIN	+5 dB -5 dB +5 dB				
PEQ2 FREQ	1600 Hz 16000 Hz				
PEQ2 Q	1.0 1.0				
PEQ2 GAIN	0 dB 0 dB				
LO-PASS FREQ	116 Hz 600 Hz				
LO-PASS RESP	4th LW 2nd LW				
HISHELV FREQ	8800 Hz				
HISHELV SLOPE	6 dB				
HISHELV GAIN	+3 dB				
DELAY ALIGNM	0 us 0 us 0 us				2 ms
POLARITY	+ + + +				
OUTPUT GAIN	+3 dB +2 dB -2 dB 0 dB				
LIMIT THRESH	21 dBu 21 dBu 21 dBu				
LIMIT DECAY	50 dB/s 50 dB/s 50 dB/s				
LIMIT HOLD	0 ms 0 ms 0 ms				
ILO & CH4 MODE					L/R